

HMC-2000 INTEVIO CONTROLLER

- Built-in speaker for audio channel monitor.
- Temporary recording function for instant message recording and broadcasting.
- Audio line to facilitate BGM from an external audio source
- Separate volume controller for mic input, line-in and speaker.
- 8 freely programmable buttons
- Expandable with X-K4/X-K8 keypad modules if required.
- Automatic fault detection.
- CAT5 cable connection with HCU-2000, max. distance is 1000m.
- Powered by HCU-2000 or external power.
- Up to 6 HMC-2000 can be connected in one system
- 8 free configurable buttons, expandable with keypad X-K4/X-K8
- Built-in loudspeaker for audio monitoring
- With 1 line input to connect with external audio source
- Supports temporary record and playback



ABOUT THE INTEVIO PUBLIC ADDRESS AND VOICE ALARM RANGE

Honeywell's INTEVIO Public Address and Voice Alarm system is the ideal solution for single buildings. It is an integrated solution that can provide better stability, cost savings, and higher user experience and performance:

DESCRIPTION

HMC-2000 is the call station for the INTEVIO system which allows user to deliver live paging and trigger background music, service broadcast or emergency broadcast to the selected speaker groups. It can also be used for volume control, temporary recording and audio monitoring, etc. Up to 6 call stations can be connected together in the system.

FUNCTIONS

Buttons

HMC-2000 has 8 functional buttons and 8 free configurable buttons. The functional buttons are used for regular functions such as all call, zone close, audio monitoring, temporary recording, recording playback, line input selection and microphone switch. The configurable buttons can be programmed as speaker group selection, broadcast task selection or volume control. The operation mode of the buttons can be configured as press or toggle. More buttons can be added by connecting extension keypad X-K4 and X-K8.

Audio monitoring

HMC-2000 has the built-in monitoring speaker to monitor the audio source in channel 1 and channel 2, which helps prevent mistaken broadcasting and increase operation efficiency.

Record and play

HMC-2000 allows user to record the temporary messages and broadcast it immediately without configuration. It's a function for operation efficiency improvement, especially for the application such as shopping mall/supermarket where the promotion message needs to be frequently updated.

Fault detection and status indication

HMC-2000 can detect the fault of the goose neck microphone and communication line. It has 4 LED indicators to show different status of the unit: power supply, general fault, network fault and busy audio channel.

Line input

With one line input, HMC-2000 allows user to connect the external audio source such as CD, DVD, tuner, etc. and broadcast it without configuration.

Technical Specification

power supply voltage	DC 24V
----------------------	--------

Rated power	10 W
-------------	------

Mic Input

Input sensitivity	5mV
-------------------	-----

Input impedance	600Ω
-----------------	------

Frequency response	100 Hz -10KHz
--------------------	---------------

SNR	>77dB, A weighted
-----	-------------------

THD	<0.5%
-----	-------

Optimal pickup distance	10~20cm
-------------------------	---------

Line Input

Input signal	1V(0dBV)
--------------	----------

Input impedance	10 KΩ
-----------------	-------

Frequency response	50Hz-18KHz
--------------------	------------

SNR	>90dB, A weighted
-----	-------------------

OTHERS

Monitoring loudspeaker	2W/8Ω
------------------------	-------

OPERATING CONDITIONS

Humidity	< 95%, without condensation
----------	-----------------------------

Operating temperature	--10°C~+55°C(14°F to +131°F)
-----------------------	------------------------------

Storage temperature	-40Â°C~+70Â°C (-40Â°F~+158Â°F)
---------------------	--------------------------------

WEIGHTS AND DIMENSIONS

Product dimension (W×H×D)	200 × 46.5 × 200 mm
---------------------------	---------------------

Package dimension (W×H×D)	403 × 133 × 268mm
---------------------------	-------------------

Net weight	1.4Kg
------------	-------

Gross weight	2.5Kg
--------------	-------

Certifications and Approvals

Category	Region	Certification
Safety	Europe	CE Certified
Safety	Global	CB Certified

Ordering Information

Description	Ordering Information
Call Station	HMC-2000

For more information,

<https://honeywellbuildings.in>

Call: 1-800-103-0339

Email: HBT-Indiabuildings@honeywell.com

Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43,
Block C, Sushant Lok Phase - I,
Gurgaon - 122002