

# X-DA1500

# HIGH EFFICIENCY

# POWER AMPLIFIER

- One channel 500W high efficiency Class-D amplifier
- Automatic protection
- Fault detection
- Effective ventilation using forced air cooling fan
- CE certification complied



## PRODUCT DESCRIPTION

X-DA1500 High Efficiency Power Amplifier (abbr. X-DA) provides amplification for audio signal delivered by high power loudspeakers that are connected to X-618 Digital Public Address and Voice Alarm System. A CE certification complied digital power amplifier certified by CCCF. X-DA1500 is reliable, efficient and light in weight.

## FEATURES

### Input/ Output

X-DA1500 supports both balanced and unbalanced audio inputs. To receive unbalanced audio inputs, simply connect the ground port with the negative input port to the rear panel.

X-DA1500 can receive audio signal from XDCS2000/ EN via Ethernet through the RJ45 standard port.

### Fault Detection

X-DA1500 can self-protect from overheat, overcurrent, overvoltage and undervoltage. For example, when the internal temperature reaches its critical limit, the over-heat protection circuit will shut down the power amplification module and activate the protection indicator light on the front panel.

X-DA1500 can detect power supply errors automatically during operation. The built-in fuse will provide overcurrent protection to the main power supply.

When a short circuit is detected in the main power supply circuit, the power will be automatically shut down. The backup power supply will then be enabled to replace the main one.

When a fault, self-protection or self-testing happens, its audio input fault port on the rear panel will short circuit and a fault signal will then be sent to the control unit in the network.

### Safety

The device adopts lightweight design. The front panel is made of UL94V-0 fire proof ABS material,

protecting the machine under extreme conditions. A cooling fan is equipped for heat exhaustion so that the machine can maintain high working efficiency.

### Volume Control

When HN-D32N Noise Detector is installed, X-DA can adjust volume according to the ambient noise automatically to ensure high sound intelligibility.

## Technical Specifications

Nominal output power	1 ×500 W
Main power supply voltage	~ 220V°240V, 50/60Hz
Backup power supply voltage	~ 220V°240V, 50/60Hz
Power consumption	< 720 W
Main power supply protection	T10 AL 250 V
Seaker output voltage	100 V / 70 V
Frequency response	70 Hz °18 KHz (+1 dB ~ °3 dB)
Input sensitivity	1.414VRMS
Impedance	20 KΩ
SNR	>100 dB(with AWeight)
Non-linear distortion	<0.05% (at 1/3 rated power, 1 KHz)
Indicator lights	Power indicator light Main power fault light Backup power fault light Signal lights Peak clipping lights Equipment protection lights
Number of channels	1
Operating conditions	95 % humidity, 0 °C ~+40 °C (0 ~ 104 F)(no condensation)
Storage temperature	°10 °C~ +55 °C (14°F~131°F)
Cooling method	Air cooling
Product dimensions (W×H×D)	416mm × 88mm × 483 mm
Package dimensions (W×H×D)	489mm × 186mm × 568 mm
Net weight	11.2 Kg
Gross weight	14.4 Kg

## Certification and Standard

Category	Region	Certification
Safety	Europe	CE Complied
	China	CCC (GB 8898)
Voice Alarm	Europe	EN 54 (Part 16) Complied
	China	CCCF (GB 16806°2006)
Material	USA	UL94V° 0 Fire-proof ABS material

## Parts included

Component	Quantity
X°DA1500 High Efficiency Power Amplifier	1
Network cable	1
Input cable terminal	1
Output cable terminal	1
AC power cable	1
Power connector kit	2
Fuse (10A)	1
Plastic foot	4
Warranty card	1
Quality certificate	1
Product manual	1
Rack	2

## Indicator Lights

Power light  
AC fault light and 1 DC fault light  
Signal light (for each channel)  
Clip light (for each channel)  
Protection light (for each channel)

## Components

Power switch

## Interfaces

Main power and backup power port  
Audio inputs (balanced or unbalanced)  
Audio outputs (100V or 70V)  
RJ<sup>®</sup>45 net cable port

## Ordering Information

Description	Ordering Information
X-DA1500 High Efficiency Power Amplifier 1×500W	X-DA1500

### For more information,

<https://honeywellbuildings.in>

Call: 1-800-103-0339

Email: [HBT-Indiabuildings@honeywell.com](mailto:HBT-Indiabuildings@honeywell.com)

### Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43,  
Block C, Sushant Lok Phase - I,  
Gurgaon - 122002