HMC-K8 EXTENSION KEYPAD

- Power supply from RK-MIC
- Flexible label slot with changeable labels
- Support rack mount or desktop flush mount
- Eight configurable keys
- Each RK-MIC can connect up to 8 extension keypads
- EN54-16, CE & CB Complied
- A two-color LED indicator for each key



DESCRIPTION

The extension Keypad is designed for the Remote Call Station RK-MIC to increase its number of physical keys. It can help users to efficiency of manual operation. The function of the keys can be configured improve the as zone selection, group selection, broadcast task selection, volume control or zone close, etc. Each Remote Call Station can connect up to 8 units of HMC-K8 and each HMC-K8 has 8 Keys and 8 indicators LEDs.

FUNCTIONS

The function of the keys on HMC-k8 can be configured as:

- Zone selection. Each zone represents one speaker line.
- Group selection. Each group represents multiple speaker lines.
- Broadcast task selection. The operation mode of the keys can be configured press or toggle.
- Volume control
- Zone Close

For different key functions, the LED indicators display differently. When the key is configured as zone/group selection, the LEDs can indicate the selection status, fault and working status. When the key is configured as broadcast task, the LEDs can indicate the broadcast status of the task.

Technical Specifications	
Power consumption	1W
Power Supply Voltage	DC 5V
No. of Indicators	8 two-color LEDs
No. of Keys	8 configurable keys
Connections	Serial data and power connection via hidden flat cable
Operating Temperature	-10°C ~ +55°C
Storage Temperature	-40°C ~ +70°C
Humidity	95%, without condensation

Dimensions(Width/ Height/Depth)	100mm × 46.5mm × 200mm
Packing Dimension (W × H × D)	403mm × 133mm × 268mm
Net weight	0.57 Kg
Gross weight	1.2 Kg

Ordering Information		
Description	Ordering Information	
Extension Keypad	HMC-K8	

For more information,

https://honeywellbuildings.in Call: 1-800-103-0339 Email: HBT-Indiabuildings@honeywell.com

Honeywell HBT India Buildings

Unitech Trade Center, 5th Floor, Sector-43, Block C, Sushant Lok Phase - I, Gurgaon - 122002

